



ООО «ХоумНэт»
www.hm-net.ru
тел. +7(3952) 55-88-88

Инструкция для Терминала HN-T17



1. Описание документа

1.1. Цель этого руководства

Данное руководство является руководством пользователя системы Digital Evidence Management System, чтобы помочь оператору программного обеспечения быстро и удобно использовать эту систему.

Предполагаемые читатели этого руководства - конечный пользователь, системный администратор, специалисты по установке и обслуживанию системы.

1.2. Область применения

Данное руководство предназначено для конечного пользователя системы управления. Мы предполагаем, что пользователь, обладающий базовыми навыками работы на компьютере, знаком с операционной средой Windows и освоил основные методы работы с программным обеспечением и базовое использование браузера Internet Explorer.

1.3. О структуре

Эта инструкция состоит из документации, системных настроек и работы системного функционального модуля. Для пользователей есть подробное описание использования этой системы во второй главе, пожалуйста, внимательно прочитайте ее перед использованием.

2. Системные настройки

Включите Терминал в сеть питания 220В, и подключите Терминал к USB разъему ПК.

2.1. Настройка места для хранения

Если вы устанавливаете программу в первый раз, пожалуйста, укажите место для хранения программы (по умолчанию: Диск E).

Первый шаг: введите пароль


(по умолчанию: администратор "admin" и первоначальный пароль: 888)

Введите логин пользователя и пароль.

Второй шаг: нажмите кнопку «Параметры» справа от меню

The screenshot displays the main interface of the software. At the top, a navigation bar contains icons for 'Review Files', 'Reports', 'Log', 'Division', 'Personnel', 'Security', 'Options', and 'Exit'. The 'Options' icon is highlighted with a red box and a red arrow. Below the navigation bar is a grid of 12 device status panels, numbered 01 to 12. Each panel contains fields for 'Device ID', 'Officer ID', 'Time', 'Size', and 'Quantity'. At the bottom of the main interface, a status bar shows 'Local IP Address: 192.168.3.185', 'Time: 2019-02-12 15:07:49', 'Version: 1.00.09', and disk usage statistics: 'Total Disk Capacity: 175.78G', 'Space used: 66.69G', and 'Space Available: 109.09G'. Below this, a 'Parameter - Settings interface' is open, showing tabs for 'Setting Docking', 'Basic information', and 'About subtasks'. The 'Advanced Options' tab is selected, displaying settings for 'File storage method', 'Files index saved server', 'Serial No.', 'Docking Station Settings', and 'Upload File Type'.

Parameter - Settings interface / Параметры - Настройки интерфейса




Примечание: если на вашем компьютере нет диска E, выберите другой диск.

2.2. Удаление файлов

А. Система док-станции удалит самый старый файл, когда на вашем компьютере нет свободного места. Терминал может удалить несколько файлов.

Б. Автоматическая очистка файла.

Система удалит все просроченные файлы и освободит намного больше памяти, когда произойдет событие. Дату можно установить в базовой функции информатизации.




В. Ручная очистка пространства


2.3. Настройка прав доступа

Если в вашем подразделении есть отделы, и каждому сотруднику отдела запрещено делиться видеофайлами. Вы должны установить:

Первый шаг: войти в систему



Второй шаг: настройка отдела



Интерфейсная схема управления отделом

Выберите 01 XX подразделение, нажмите «изменить», чтобы изменить название (Примечание: первый отдел является основным подразделением, это системное подразделение по умолчанию, вы можете изменить название отдела на свой номер отдела, но вы можете не удалять его), другой отдел можно создать под основным подразделением.

Review Files Reports Log Division Personnel Security Options Exit

Add Modify Delete Export Close

Dept Name: Search

No.	Dept No	department	Parent Department	Date Created	Created by	Memo
1	10001	XX Division		2018-2-1	fff	
2	333	4444	XX Division	2018-7-4	admin	

Dept Number2

Local IP Address: 192.168.3.185 Time: 2019-02-12 16:14:01 Total Disk Capacity: 175.78G Space used: 66.69G Space Available: 109.09G 37.94%

Version: 1.00.09

Создать отдел:

Review Files Reports Log Division Personnel Security Options Exit

Add Modify Delete Export Close

Dept Name: Search

No.	Dept No	department	Parent Department	Date Created	Created by	Memo
1	10001	XX				
2	333	44				

Dept Number2

Local IP Address: 192.168.3.185 Time: 2019-02-12 16:15:04 Total Disk Capacity: 175.78G Space used: 66.69G Space Available: 109.09G 37.94%

Version: 1.00.09

Department Details

Dept No: 333 Dept Name: 4444

Parent Department: XX Division

Memo:

Created by: admin Created by: 2019-2-12

Department Details

Dept No: 333 Dept Name: 4444

Parent Department: XX Division

Memo:

Created by: admin Created by: 2019-2-12

← Back → Next SaveAdd Confirm Cancel

Примечание: вы должны выбрать «родительский» отдел.

2.4. Настройка ID сотрудника

Если вы хотите, чтобы все файлы, которые были записаны камерой, показывали информацию о камере и информацию о сотруднике, вы должны привязать информацию к персональному видеорегистратору.


Сначала выберите отдел

Review Files Reports Log Division **Personnel** Security Options Exit


01 Device ID: <input type="text"/> Officer ID: <input type="text"/> Officer: <input type="text"/> Time: <input type="text"/> Size: <input type="text"/> Quantity: <input type="text"/>	02 Device ID: <input type="text"/> Officer ID: <input type="text"/> Officer: <input type="text"/> Time: <input type="text"/> Size: <input type="text"/> Quantity: <input type="text"/>	03 Device ID: <input type="text"/> Officer ID: <input type="text"/> Officer: <input type="text"/> Time: <input type="text"/> Size: <input type="text"/> Quantity: <input type="text"/>	04 Device ID: <input type="text"/> Officer ID: <input type="text"/> Officer: <input type="text"/> Time: <input type="text"/> Size: <input type="text"/> Quantity: <input type="text"/>
05 Device ID: <input type="text"/> Officer ID: <input type="text"/> Officer: <input type="text"/> Time: <input type="text"/> Size: <input type="text"/> Quantity: <input type="text"/>	06 Device ID: <input type="text"/> Officer ID: <input type="text"/> Officer: <input type="text"/> Time: <input type="text"/> Size: <input type="text"/> Quantity: <input type="text"/>	07 Device ID: <input type="text"/> Officer ID: <input type="text"/> Officer: <input type="text"/> Time: <input type="text"/> Size: <input type="text"/> Quantity: <input type="text"/>	08 Device ID: <input type="text"/> Officer ID: <input type="text"/> Officer: <input type="text"/> Time: <input type="text"/> Size: <input type="text"/> Quantity: <input type="text"/>
09 Device ID: <input type="text"/> Officer ID: <input type="text"/> Officer: <input type="text"/> Time: <input type="text"/> Size: <input type="text"/> Quantity: <input type="text"/>	10 Device ID: <input type="text"/> Officer ID: <input type="text"/> Officer: <input type="text"/> Time: <input type="text"/> Size: <input type="text"/> Quantity: <input type="text"/>	11 Device ID: <input type="text"/> Officer ID: <input type="text"/> Officer: <input type="text"/> Time: <input type="text"/> Size: <input type="text"/> Quantity: <input type="text"/>	12 Device ID: <input type="text"/> Officer ID: <input type="text"/> Officer: <input type="text"/> Time: <input type="text"/> Size: <input type="text"/> Quantity: <input type="text"/>

Local IP Address: 192.168.3.185 Time: 2019-02-12 16:34:51 Total Disk Capacity: 175.78G Space used: 66.69G Space Available: 109.09G 37.94%

Version: 1.00.09



Второй шаг: добавьте сотрудника и выберите камеру для него.



3. Загрузка файлов с персонального регистратора

Откройте программу, вставьте персональный регистратор в терминал. Он будет загружать файлы автоматически.

Review Files Reports Log Division Personnel Security Options Exit

01 Device ID: 6A05698 Officer ID: Officer: Time: 00:00:22 Size: 105.94 MB Quantity: 2 F:\0190212170834_0001.MP4-->E\	02 Device ID: Officer ID: Officer: Time: Size: Quantity:	03 Device ID: Officer ID: Officer: Time: Size: Quantity:	04 Device ID: Officer ID: Officer: Time: Size: Quantity:
05 Device ID: Officer ID: Officer: Time: Size: Quantity:	06 Device ID: Officer ID: Officer: Time: Size: Quantity:	07 Device ID: Officer ID: Officer: Time: Size: Quantity:	08 Device ID: Officer ID: Officer: Time: Size: Quantity:
09 Device ID: Officer ID: Officer: Time: Size: Quantity:	10 Device ID: Officer ID: Officer: Time: Size: Quantity:	11 Device ID: Officer ID: Officer: Time: Size: Quantity:	12 Device ID: Officer ID: Officer: Time: Size: Quantity:

Local IP Address: 192.168.3.185 Time: 2019-02-12 17:11:19 Total Disk Capacity:175.78G Space used:66.69G Space Available:109.09G 37.54%

Version: 1.00.09

Загрузка файлов

Review Files Reports Log Division Personnel Security Options Exit

01 Device ID: 6A05698 Officer ID: Officer: Time: 00:00:00 Size: 0.00 MB Quantity: 0 F\	02 Device ID: Officer ID: Officer: Time: Size: Quantity:	03 Device ID: Officer ID: Officer: Time: Size: Quantity:	04 Device ID: Officer ID: Officer: Time: Size: Quantity:
05 Device ID: Officer ID: Officer: Time: Size: Quantity:	06 Device ID: Officer ID: Officer: Time: Size: Quantity:	07 Device ID: Officer ID: Officer: Time: Size: Quantity:	08 Device ID: Officer ID: Officer: Time: Size: Quantity:
09 Device ID: Officer ID: Officer: Time: Size: Quantity:	10 Device ID: Officer ID: Officer: Time: Size: Quantity:	11 Device ID: Officer ID: Officer: Time: Size: Quantity:	12 Device ID: Officer ID: Officer: Time: Size: Quantity:

Local IP Address: 192.168.3.185 Time: 2019-02-12 17:11:56 Total Disk Capacity:175.78G Space used:66.8G Space Available:108.98G 38%


Version: 1.00.09

4. Просмотр файлов

Вы можете искать файл по идентификатору регистратора, имени сотрудника, дате записи и т.д. Вы также можете воспроизвести видеофайл и пометить этот файл, можете удалить файл, защитить файл, загрузить файл на свой съемный диск и т.д.


4.1. Поиск файлов


Пожалуйста, введите условие запроса и нажмите кнопку «Поиск».




4.2. Воспроизведение видеофайла


Выберите файл записи и нажмите кнопку «Воспроизвести».





Нажмите кнопку «Подробности» для подробной информации о файле записи.





4.3. Защита файла

Если вы хотите защитить файл, предотвратите его удаление, надо нажать кнопку «защитить» после выбора файла. Нажатие кнопки «снять защиту» - сменит статус защиты.

Review Files Reports Log Division Personnel Security Options Exit

Search Detail Play Download Burn Disc Export Import Delete Protect Unprotect Close

Device ID: [] Officer: [] Date Uploaded: 2019-2-5 To 2019-2-12 File Type: All

Main Task: All Subtask: [] Time: [] To: [] File Size: Above

Importance Level: All Dept Name: [] Note: [] Find locked files only Select All

No.	department	Device ID	Officer ID	Officer	Date Recorded	Recording time	Length [min]	Resolution	Importance Level	Keep Time	Main Task	Subtask	File
11		6A05698			2019-02-12	14:20:06	7s 140ms	1920X1080	Normal	2019-4-13 1			Vic
12		6A05698			2019-02-12	14:20:10	0.1s	1920X1080	Normal	2019-4-13 1			Ph
13		6A05698			2019-02-12	14:20:13	0.1s	1920X1080	Normal	2019-4-13 1			Ph
14		6A05698			2019-02-12	14:31:29	667ms	1920X1080	Normal	2019-4-13 1			Vic
15		6A05698			2019-02-12	14:31:35	226 89ms	1920X1080	Normal	2019-4-13 1			Vic
16		6A05698			2019-02-12	14:33:43	24s 458ms	1920X1080	Normal	2019-4-13 1			Vic
17		6A05698			2019-02-12	17:08:34	400ms	1920X1080	Normal	2019-4-13 1			Vic
18		6A05698			2019-02-12	17:08:39	2mn 27s	1920X1080	Normal	2019-4-13 1			Vic

Total Files: 8 Video: 6 Photo: 2 Audio: 0 Other: 0 Total File Size: 200.84 MB

Local IP Address: 192.168.3.185 Time: 2019-02-12 18:02:14 Total Disk Capacity: 175.78G Space used: 66.8G Space Available: 108.98G 38%

Version: 1.00.09

Review Files Reports Log Division Personnel Security Options Exit

Search Detail Play Download Burn Disc Export Import Delete Protect Unprotect Close

Device ID: [] Officer: [] Date Uploaded: 2019-2-5 To 2019-2-12 File Type: All

Main Task: All Subtask: [] Time: [] To: [] File Size: Above

Importance Level: All Dept Name: [] Note: [] Find locked files only Select All

Resolution	Importance Level	Keep Time	Main Task	Subtask	File Type	Size(MB)	Date Uploaded	Protected	Locked	Case ID	Uploaded Cloud	Note
1920X1080	Normal	2019-4-13 1			Video	20.03	2019-02-12 14:2	<input type="checkbox"/>	<input type="checkbox"/>		0.0%	
1920X1080	Normal	2019-4-13 1			Photo	0.27	2019-02-12 14:2	<input checked="" type="checkbox"/>	<input type="checkbox"/>		0.0%	
1920X1080	Normal	2019-4-13 1			Photo	0.26	2019-02-12 14:2	<input type="checkbox"/>	<input type="checkbox"/>		0.0%	
1920X1080	Normal	2019-4-13 1					14:3	<input type="checkbox"/>	<input type="checkbox"/>		0.0%	
1920X1080	Normal	2019-4-13 1					14:3	<input type="checkbox"/>	<input type="checkbox"/>		0.0%	
1920X1080	Normal	2019-4-13 1					14:3	<input type="checkbox"/>	<input type="checkbox"/>		0.0%	
1920X1080	Normal	2019-4-13 1					17:1	<input type="checkbox"/>	<input type="checkbox"/>		0.0%	
1920X1080	Normal	2019-4-13 1					17:1	<input type="checkbox"/>	<input type="checkbox"/>		0.0%	

Message

Selected file can not be deleted.

确定


Файл защищен от удаления

Total Files: 8 Video: 6 Photo: 2 Audio: 0 Other: 0 Total File Size: 200.84 MB

Local IP Address: 192.168.3.185 Time: 2019-02-12 18:04:50 Total Disk Capacity: 175.78G Space used: 66.8G Space Available: 108.98G 38%

Version: 1.00.09

4.4. Загрузка файла на другой диск




4.5. Записать видео файла на CD/DVD диск


Если вы хотите использовать эту функцию, вам нужно проверить, есть ли на вашем ПК DVD-привод для перезаписи.

4.6. Импорт файлов

Вы можете импортировать видеофайлы в базу данных. Система может управлять другими видеофайлами, хранящимися на вашем ПК, но не загруженные терминалом.




Примечание: с зажатой клавишей «Shift» можно выбрать несколько файлов



Примечание: только структура имени файла «ID@ууууммддhhmmss.xxx» может быть идентифицирована и импортирована в базу данных.

5. Отчеты

Функция отчета предоставляет только общую информацию.



Review Files Reports Log Division Personnel Security Options Exit

Search Export Close

Officer ID: [] Date Uploaded: 2019-11-5 To 2019-2-12

Officer: [] Dept Name: []

Statistics by office | Uploaded by department | Playback Frequency

No.	Officer ID	Officer	All Files	Video length [min]	Audio length [min]	Photos
1	000000	000000				
2	000045	000045				
3	000043	000043				
4	000003	000003				
5	000000	000000				
6	300004	200003				
7	300004	400003				
8	300004	300004				
9	000000	000000				
10	000004	000004				

Local IP Address: 192.168.3.185 Time: 2019-02-12 18:38:08 Version: 1.00.09

Total Disk Capacity: 175.78G Space used: 66.8G Space Available: 108.98G 38%

6. Логи

Логирование

Review Files Reports Log Division Personnel Security Options Exit

Search Export Close

01 Device ID: [] Officer ID: [] Officer: [] Time: [] Size: [] Quantity: []

02 Device ID: [] Officer ID: [] Officer: [] Time: [] Size: [] Quantity: []

03 Device ID: [] Officer ID: [] Officer: [] Time: [] Size: [] Quantity: []

04 Device ID: [] Officer ID: [] Officer: [] Time: [] Size: [] Quantity: []

05 Device ID: [] Officer ID: [] Officer: [] Time: [] Size: [] Quantity: []

06 Device ID: [] Officer ID: [] Officer: [] Time: [] Size: [] Quantity: []

07 Device ID: [] Officer ID: [] Officer: [] Time: [] Size: [] Quantity: []

08 Device ID: [] Officer ID: [] Officer: [] Time: [] Size: [] Quantity: []

09 Device ID: [] Officer ID: [] Officer: [] Time: [] Size: [] Quantity: []

10 Device ID: [] Officer ID: [] Officer: [] Time: [] Size: [] Quantity: []

11 Device ID: [] Officer ID: [] Officer: [] Time: [] Size: [] Quantity: []

12 Device ID: [] Officer ID: [] Officer: [] Time: [] Size: [] Quantity: []

Local IP Address: 192.168.3.185 Time: 2019-02-12 18:44:12 Version: 1.00.09

Total Disk Capacity: 175.78G Space used: 66.8G Space Available: 108.98G 38%

Review Files Reports Log Division Personnel Security Options Exit

Search Delete **Export** Close

Officers: [] Event Types: [] Operate Time: 2019-2-9 To: 2019-2-12
 Event Content: [] IP Address: []

Date Created	Event	Event Content	Parent Department	User	IP Address
2019-2-12 18:45:27	Using the module funct	Log	XX Division	admin	192.168.3.185
2019-2-12 18:43:53	Using the module funct	Log	XX Division	admin	192.168.3.185
2019-2-12 18:43:51	Login system		XX Division	admin	192.168.3.185
2019-2-12 18:42:31	Using the module funct	Log	XX Division	admin	192.168.3.185
2019-2-12 18:42:26	Using the module funct	Review Files	XX Division	admin	192.168.3.185
2019-2-12 18:37:39	Using the module funct	Reports	XX Division	admin	192.168.3.185
2019-2-12 18:36:59	Using the module funct	Reports	XX Division	admin	192.168.3.185
2019-2-12 18:36:46	Login system		XX Division	admin	192.168.3.185
2019-2-12 18:30:34	Unprotect		XX Division	admin	192.168.3.185
2019-2-12 18:30:34	Unprotect	6A05698@2019021214201310.jpg	XX Division	admin	192.168.3.185
2019-2-12 18:30:34	Unprotect	6A05698@2019021214334310.mp4	XX Division	admin	192.168.3.185
2019-2-12 18:30:34	Unprotect	6A05698@2019021214313510.mp4	XX Division	admin	192.168.3.185
2019-2-12 18:30:34	Unprotect	6A05698@2019021217083410.mp4	XX Division	admin	192.168.3.185
2019-2-12 18:30:27	Protect files	6A05698@2019021214313510.mp4	XX Division	admin	192.168.3.185
2019-2-12 18:30:27	Protect files	6A05698@2019021214312910.mp4	XX Division	admin	192.168.3.185
2019-2-12 18:30:27	Protect files	6A05698@2019021214201310.jpg	XX Division	admin	192.168.3.185
2019-2-12 18:30:27	Protect files	6A05698@2019021214334310.mp4	XX Division	admin	192.168.3.185
2019-2-12 18:30:27	Protect files	6A05698@2019021217083410.mp4	XX Division	admin	192.168.3.185

Records: 231

Local IP Address: 192.168.3.185 Time: 2019-02-12 18:45:28 Total Disk Capacity: 175.78G Space used: 66.8G Space Available: 108.98G 38%

Version: 1.00.09

Примечание: журналы автоматически очищаются с интервалом времени около 6 месяцев.

7. Безопасность

Функция предоставляется администратору для управления логинами пользователей.

Review Files Reports Log Division Personnel **Security** Options Exit

01 Device ID: [] Officer ID: [] Officer: [] Time: [] Size: [] Quantity: []

02 Device ID: [] Officer ID: [] Officer: [] Time: [] Size: [] Quantity: []

03 Device ID: [] Officer ID: [] Officer: [] Time: [] Size: [] Quantity: []

04 Device ID: [] Officer ID: [] Officer: [] Time: [] Size: [] Quantity: []

05 Device ID: [] Officer ID: [] Officer: [] Time: [] Size: [] Quantity: []

06 Device ID: [] Officer ID: [] Officer: [] Time: [] Size: [] Quantity: []

07 Device ID: [] Officer ID: [] Officer: [] Time: [] Size: [] Quantity: []

08 Device ID: [] Officer ID: [] Officer: [] Time: [] Size: [] Quantity: []

09 Device ID: [] Officer ID: [] Officer: [] Time: [] Size: [] Quantity: []


10 Device ID: [] Officer ID: [] Officer: [] Time: [] Size: [] Quantity: []

11 Device ID: [] Officer ID: [] Officer: [] Time: [] Size: [] Quantity: []

12 Device ID: [] Officer ID: [] Officer: [] Time: [] Size: [] Quantity: []


Local IP Address: 192.168.3.185 Time: 2019-02-12 19:00:13 Total Disk Capacity: 175.78G Space used: 66.8G Space Available: 108.98G 38%

Version: 1.00.09



7.1. Новый пользователь

Нажмите «Добавить»



1. Для нового пользователя надо ввести ID, имя, отделение, пароль.
2. Пароль должен быть 6 знаков с содержанием цифр и букв.

7.2. Права пользователя

1. Зайдите под правами администратора

The screenshot shows a software interface with a top navigation bar containing icons for Review Files, Reports, Log, Division, Personnel, Security, Options, and Exit. Below this is a toolbar with buttons for Add, Modify, Cancel, Delete, and Close. The main area is divided into two panes. The left pane shows a tree view with 'XX Division' and '4444'. The right pane contains a table with the following data:

Officer ID	Officer	Parent Department	Available
admin	admin	XX Division	<input checked="" type="checkbox"/>
333	uuu3	XX Division	<input checked="" type="checkbox"/>
sfsf	sdfsdf	XX Division	<input checked="" type="checkbox"/>
ddd	ddd	XX Division	<input checked="" type="checkbox"/>

To the right of the table is a 'Permission settings' panel with a list of permissions, all of which are checked:

- All:
- Review Files
- Setting Docking ...
- Reports
- Log
- Division
- Personnel
- Security
- Options ...
- Docking Station ...
- Permit data deletion ...
- Permit file download ...
- Permit file Lock ...
- Permit file review ...
- View Own Data Only
- Permit Unlock
- Permit Unprotect

At the bottom, there is a status bar with the following information: Local IP Address: 192.168.3.185, Time: 2019-02-12 19:12:37, Total Disk Capacity: 175.78G, Space used: 66.8G, Space Available: 108.98G, 38%, and Version: 1.00.09.

2. Выберите необходимую функцию "√".

This screenshot is identical to the one above, but the row for officer '333' (uuu3) in the table is highlighted with a red border. The rest of the interface, including the permission settings panel and status bar, remains the same.

8. Изменение пароля

При изменении пароля необходимо указать старый, а затем новый и его подтверждение.

The image shows two screenshots of the 'Digital Docking Station System' interface. The top screenshot shows the main dashboard with a grid of 12 docking stations (01-12) and system status information. A red box highlights the 'Change Password' icon in the top right corner. The bottom screenshot shows the same dashboard with a 'Change Password' dialog box open in the center. The dialog box contains four input fields: 'User Name', 'Old Password', 'New Password', and 'Confirm New Password'. The 'New Password' and 'Confirm New Password' fields are highlighted with a red box. The system status bar at the bottom of both screenshots shows: Local IP Address: 192.168.3.185, Time: 2019-02-12 19:16:08, Version: 1.00.09, Total Disk Capacity: 175.78G, Space used: 66.8G, Space Available: 108.98G, 38%.

Digital Docking Station System

01 Device ID: Officer ID: Officer: Time: Size: Quantity:

02 Device ID: Officer ID: Officer: Time: Size: Quantity:

03 Device ID: Officer ID: Officer: Time: Size: Quantity:

04 Device ID: Officer ID: Officer: Time: Size: Quantity:

05 Device ID: Officer ID: Officer: Time: Size: Quantity:

06 Device ID: Officer ID: Officer: Time: Size: Quantity:

07 Device ID: Officer ID: Officer: Time: Size: Quantity:

08 Device ID: Officer ID: Officer: Time: Size: Quantity:

09 Device ID: Officer ID: Officer: Time: Size: Quantity:

10 Device ID: Officer ID: Officer: Time: Size: Quantity:

11 Device ID: Officer ID: Officer: Time: Size: Quantity:

12 Device ID: Officer ID: Officer: Time: Size: Quantity:

Local IP Address: 192.168.3.185 Time: 2019-02-12 19:16:08 Total Disk Capacity: 175.78G Space used: 66.8G Space Available: 108.98G 38%

Version: 1.00.09

Digital Docking Station System

Change Password

01 Device ID: Officer ID: Officer: Time: Size: Quantity:

02 Device ID: Officer ID: Officer: Time: Size: Quantity:

03 Device ID: Officer ID: Officer: Time: Size: Quantity:

04 Device ID: Officer ID: Officer: Time: Size: Quantity:

05 Device ID: Officer ID: Officer: Time: Size: Quantity:

06 Device ID: Officer ID: Officer: Time: Size: Quantity:

07 Device ID: Officer ID: Officer: Time: Size: Quantity:

08 Device ID: Officer ID: Officer: Time: Size: Quantity:

09 Device ID: Officer ID: Officer: Time: Size: Quantity:

10 Device ID: Officer ID: Officer: Time: Size: Quantity:

11 Device ID: Officer ID: Officer: Time: Size: Quantity:

12 Device ID: Officer ID: Officer: Time: Size: Quantity:

User Name: Old Password: New Password: Confirm New Password:


Confirm Cancel

Local IP Address: 192.168.3.185 Time: 2019-02-12 19:16:26 Total Disk Capacity: 175.78G Space used: 66.8G Space Available: 108.98G 38%


Version: 1.00.09

9. Выход из программы

Нажмите кнопку «Выход»




В окне выбора «Перезагрузка/Выход/Отключение» введите пароль (по умолчанию: 2014, можно изменить в меню настроек)





9.1. Изменение пароля выхода из системы



Review Files Reports Log Division Personnel Security **Options** Exit

01 Device ID: Officer ID: Officer: Time: Size: Quantity:	02 Device ID: Officer ID: Officer: Time: Size: Quantity:	03 Device ID: Officer ID: Officer: Time: Size: Quantity:	04 Device ID: Officer ID: Officer: Time: Size: Quantity:
05 Device ID: Officer ID: Officer: Time: Size: Quantity:	06 Device ID: Officer ID: Officer: Time: Size: Quantity:	07 Device ID: Officer ID: Officer: Time: Size: Quantity:	08 Device ID: Officer ID: Officer: Time: Size: Quantity:
09 Device ID: Officer ID: Officer: Time: Size: Quantity:	10 Device ID: Officer ID: Officer: Time: Size: Quantity:	11 Device ID: Officer ID: Officer: Time: Size: Quantity:	12 Device ID: Officer ID: Officer: Time: Size: Quantity:

Local IP Address: 192.168.3.185 Time: 2019-02-12 15:26:37 Total Disk Capacity: 175.78G Space used: 66.69G Space Available: 109.09G **37.94%**

Version: 1.00.09

Review Files Reports Log Division Personnel Security **Options** Exit

Save Close

Setting Docking Basic information About subtasks

Wired LAN Advanced Options Notification service

File storage method
 Cover the oldest file Auto purge expired file Manual clean up space Choose a storage disk: E

Files index saved server Server: 192.168.0.65 Port: 2013

Serial No. Station ID: TF755BY93TD21S Serial No: AF25C233EA755F5D

Docking Station Settings
 Delete uploaded files Restart Docking System Password: **** Enter System Desktop password: ****

Upload File Type
 *(All Type) Obtain a frame of video


-Video
*.avi
*.mp4
*.wmv
*.mov
*.flv

-Audio
*.mp3
*.wav

-Photo
*.jpg
*.bmp
*.png
*.G2

Local IP Address: 192.168.3.185 Time: 2019-02-12 15:26:59 Total Disk Capacity: 175.78G Space used: 66.69G Space Available: 109.09G **37.94%**

Version: 1.00.09



Примечание: вы должны сохранить информацию после ввода новых параметров.